



435 P/N - 44141-A

AMPLIFIER - REPLACEMENT PARTS LIST
(L and R denotes Left and Right Channel)

Item	Description	Part No.	Item	Description	Part No.
	CAPACITORS			RESISTORS	
C1 L&R	.047 mfd 200V.	35371	R1 L&R	100,000 10%	16228
C2 L&R	4 mfd 250V.	39328	R2 L&R	1,500 ohm Lo-Noise	41155
C3 L&R	.033 mfd 200V	41333	R3 L&R	1 Meg. ohm 10%	13320
C4 L&R	.033 mfd 200V.	41333	R4 L&R	470,000 10%	13018
C5 L&R	.033 mfd 200V.	41333	R5 L&R	4,700 ohm	32832
C6 L&R	.0018 mfd Ceramic Disc.	44440	R6 L&R	75 Ohm Control - 2 Watt	36918
C7 L&R	50 mfd Ceramic Disc.	30585	R7 L&R	22 ohm	35330
C8 L&R	330 mfd Ceramic Disc.	33088	R8	7,800 ohm 25 Watt Standee	34069
C9 L&R	100 mfd Ceramic Disc.	42297	R9 L&R	4,700 ohm	32832
C10 L&R	.047 mfd 600V.	35371	R10 L&R	1,000 ohm	19187
C11 L&R	.047 mfd 600V.	35371	R11 L&R	220 ohm 10%	35632
C12 L&R	50 mfd 25V.	41151	R12 L&R	22,000 ohm	38232
C16	100 + 20 mfd 400V.	34765	R13 L&R	47,000 ohm	13015
C17	100 + 20 mfd 400V.	34765	R14 L&R	18,000	33323
C18	.1 mfd 600V.	35385	R15	Balance Control	44182
C19	250 mfd 64V.	43536	R16	Tandem Tone Control	35341
C28 L&R	.22 mfd 200V.	39471-1	R17	Tandem Tone Control-Linear	35413
C29 L&R	.15 mfd 200V.	39472-1	R18 L&R	10,000 ohm	35331
C30 L&R	.0039 mfd 200V.	42925	R19 L&R	470,000 ohm 10%	13018
	PICKUP CARTRIDGE		R20 L&R	47,000 ohm	13015
CPU1	Astatic-Ceramic	35122	R21 L&R	3,300 ohm Lo-Noise	41152
	RECTIFIERS		R22 L&R	82,000 ohm Lo-Noise	38679
CR1	600 P.R.V. Silicon Rectifier	43193	R23 L&R	47,000 ohm	13015
CR2	600 P.R.V. Silicon Rectifier	43193	R24 L&R	470,000 ohm 10%	13018
CR3	600 P.R.V. Silicon Rectifier	43193	R25 L&R	470,000 ohm 10%	13018
CR4	600 P.R.V. Silicon Rectifier	43193	R26 L&R	27,000 ohm 10%	15403
CR5	Rectifier	39670	R27 L&R	27,000 ohm 10%	15403
	FUSES		R28 L&R	130 ohm 3 Watt	32171
F1	2 Amp. 250V. Slo-Blo & Fuse Holder (Bussman)	ST-9600	R29	Dual 16 ohm "L" Pad	38703
F2	Slo-Blo Fuse 7Amp 125V. SOCKETS	ST-4347 ST-9619	R33	1,070 ohm 25 Watt Standee	41178
J1	Dual Input Socket	33199	R34	10,000 ohm 10%	13388
J2	12 Cir. Skt. Hsing	V-7021	R35	4,700 ohm 10%	16226
J3	6 Prong Min. Skt. & Ret.	18634	R36	270,000 ohm 1 Watt 10%	34904
J4	12 Cir. Mtr. Mnt. Pin Hsg.	V-7042	R37	2,200 ohm 10%	35475
	MISCELLANEOUS		R38	75 ohm Control - 2 Watt	36918
K1	Stereo Muting Relay	33263	R39	220 ohm 1 Watt 10%	35326
P1	Dual Input Plug	34536-3	R42	Dual Volume Potentiometer	39469
P3	6 Prong Min. Plug & Shell	18633	R43 L&R	1,500 ohm	32830
P.E.C.1	Dual Input P.E.C.	35386	R44 L&R	1,500 ohm	32830
	TUBES			SWITCHES	
V1	12AU7/ECC82 Tube	35365	S2	DPDT Slide Switch	31192
V2 L&R	6CY7 Vacuum Tube	32498	S3	SPDT Slide Switch	30277
V3 L&R	12AT7/ECC81 Tube	34773	S4	4 Position Switch	36919
V4 L&R	6BQ5/EL84 Tube	32141	S6	DPDT Slide Switch	40510
V5 L&R	6BQ5/EL84 Tube	32141		TRANSFORMERS	
			T1 L&R	Output Transformer	41144
			T2	Amplifier Power Transformer	41146
				THERMISTOR	
			TH1 L&R	Thermistor	34225