



STEREO AMPLIFIER No. 48350-1A PARTS LIST — Continued
(L and R denotes Left and Right Channel)

Item	Description	Part No.	Item	Description	Part No.
RESISTORS (Continued)			SWITCHES		
R44 L	22 ohm 2W 10%	49298	S1	Slide Switch DPDT	49302
R45 L	10K 10%	13388	S2	Slide Switch DPDT	49302
R46	2W 10%	49719	S3	Slide Switch DPDT	49302
R47 L	2.3K 10%	18660	S4	2 Pole 2 Pos. Switch	49281
R48 R	3.3K 10%	18660	S5 L	2 Pole 3 Pos. Switch	49280
DIODES AND RECTIFIERS			S6 R	2 Pole 3 Pos. Switch	49280
CR1 L	AVC Diode	49141	S7 L	2 Pole 3 Pos. Switch	49280
CR2 L	AVC Diode	49141	S8 R	2 Pole 3 Pos. Switch	49280
CR3 R	AVC Diode	49141	S9	Momentary Push Switch	44772
CR4 R	AVC Diode	49141	MISCELLANEOUS		
CR5 L	Reference Diode	49140	TC1 LR	Thermostat	49295
CR6 R	Reference Diode	49140	F1	Fuse Holder	47837
CR7	100 PRV 1 Amp Sil. Rect.	46497	L1	Lamp Holder with Lens	49318
CR8 L&R	100 PRV 1 Amp Sil. Rect.	46497	L2	Type #313 Bulb	ST-3059
CR9 L&R	Reference Diode	49140	J1	3 Pin Socket	44927
CR10 R	100 PRV 1 Amp Sil. Rect.	46497	J2 L&R	IC Socket — 8 Pin	49273
CR11 L	100 PRV 1 Amp Sil. Rect.	46497	J3	6 Prong Min. Soc. (Ret. ST-9817)	18634
CR12	100 PRV 1 Amp Sil. Rect.	46497	J4	Mute Relay Socket (not shown)	49282
CR13	100 PRV 1 Amp Sil. Rect.	46497	K1	Mute Relay	43561
CR14	15V 1W Zener Diode	46617	K2	Relay 2PDT-24V	48213
CR15	15V 1W Zener Diode	46617	P1	Dual Input Cable Assembly	49546-A
CR16	100 PRV 1 Amp Sil. Rect.	46497	P2	6 Pin Molded Plug & Cable	49294
CR17	6 Amp 200V Rectifier	49293	PEC1 L&R	Pre Amp Circuit	48937
CR18	6 Amp 200V Rectifier	49293	PEC2 L&R	Pre Amp Circuit	48940
CR19	100 PRV 1 Amp Sil. Rect.	46497	PEC3	AVC Circuit	48936
CR20	100 PRV 1 Amp Sil. Rect.	46497	PEC4 L&R	Driver Circuit	48943
INTEGRATED CIRCUIT COMPONENT			PEC5	Volume Control	44715
IC L&R	Dual Integrated Circuit	48934	PEC6	Scratch Filter Circuit	48946
TRANSISTORS			PU1	Magnetic Cartridge (M44MR)	43467
Q1 L	MPSA56	47831	AMPLIFIER CONNECTORS		
Q2 R	MPSA56	47831		2 Circuit Post Housing	49289
Q3 L&R	MPSA56	47831		2 Circuit Post Connector	49274
Q4 L&R	MPSU05	49139		3 Circuit Min. Plug	49144
Q5 L&R	Power Tab Transistor N.P.N.	48929		6 Circuit Min. Plug	48102
Q6 L&R	Power Tab Transistor P.N.P.	48932		6 Circuit Min. Receptacle	48153
Q7 L&R	Power Transistor N.P.N.	48931		6 Circuit Post Housing	49319
Q8 L&R	Power Transistor N.P.N.	48931		8 Circuit Post Housing	49290
Q9	Transistor MPS-A06	49415		8 Circuit Post Connector	49275
TRANSFORMERS				10 Circuit Post Housing	49291
T1	Autoformer 50 V.C.T.	49300		10 Circuit Post Housing	49276
T2 L&R	Speaker Output Transformers	49096		12 Circuit Min. Plug	48109
				12 Circuit Min. Receptacle	48104
				14 Circuit Post Housing	49292
				14 Circuit Right Angle Connector	49277
				Pin (Min. Plug)	48116
				Socket (Min. Receptacle)	48114