

1094/5

M U S T A C H E B O Y

<u>Solder Side</u>		<u>Parts Side</u>
GND	1	GND
GND	2	GND
+5V	3	+5V
+5V	4	+5V
-5V	5	-5V
+12V	6	+12V
	7	
COIN COUNTER 2	8	COIN COUNTER 1
	9	
SPEAKER(-)	10	SPEAKER(+)
	11	
VIDEO GREEN	12	VIDEO RED
VIDEO SYNC	13	VIDEO BULE
	14	VIDEO GND
	15	
COIN SWITCH 2	16	COIN SWITCH 1
START SWITCH 2	17	START SWITCH 1
2P CONTROL UP	18	1P CONTROL UP
2P CONTROL DOWN	19	1P CONTROL DOWN
2P CONTROL LEFT	20	1P CONTROL LEFT
2P CONTROL RIGHT	21	1P CONTROL RIGHT
2P CONTROL PUSH 1	22	1P CONTROL PUSH 1
2P CONTROL PUSH 2	23	1P CONTROL PUSH 2
	24	
	25	
	26	
GND	27	GND
GND	28	GND

DIP SW 1	1	2	3	4	5	6	7	8
COIN 1 (COIN/CREDIT)								
1/1	OFF	OFF	OFF					
2/1	ON	OFF	OFF					
1/3	OFF	ON	OFF					
4/1	ON	ON	OFF					
1/2	OFF	OFF	ON					
3/1	ON	OFF	ON					
1/5	OFF	ON	ON					
5/1	ON	ON	ON					
COIN 2 (COIN/CREDIT)								
1/1				OFF	OFF			
2/1				ON	OFF			
1/2				OFF	ON			
2/3				ON	ON			
TEST MODE (NORMAL)							OFF	
" (TEST)							ON	
FREE PLAY								ON
NORMAL PLAY								OFF
SCREEN REVERSE (HARD SW)								
NORMAL SCREEN								ON
DIP SW 2								OFF
	1	2	3	4	5	6	7	8
UPLIGHT TYPE	OFF							
TABLE TYPE	ON							
DIFFICULTY 0		OFF	OFF					
1		ON	OFF					
2		OFF	ON					
3		ON	ON					
NUMBER OF PLAYER								
3				OFF	OFF			
1				ON	OFF			
2				OFF	ON			
4				ON	ON			
DEMO SOUND								ON
NO DEMO SOUND								OFF

* It is not used that any terminal does not write down. The other terminal (especially -5V) must be connected certainly.

* 3 is most difficult.

* At first the beginning, bonus point is 50000 point.