



JUL 28 1980

TAITO AMERICA CORPORATION

1256 ESTES AVENUE • ELK GROVE VILLAGE, IL 60007
(312) 981-1000 • TELEX 253290 CABLE TAMCO ELK GROVE VILLAGE

Dear Taito Distributor:

Enclosed is a copy of an article, which will appear in STAR TECH and PLAYMETER Magazines, concerning a field modification, which will eliminate a possible false credit situation. The kit part #840011 will be supplied to your Parts Department this week. One kit per each Space Chaser or Lunar Rescue that you have bought to date. We would appreciate it if you would pass this along to your customers who have Space Chaser and Lunar Rescue games as it could increase their cash box take.

Should you need additional kits or if you have any questions, please feel free to call on our Parts Department.

Very truly yours,


Bob Milchuck

Customer Service
TAITO AMERICA CORPORATION

CC: Service Department
Parts Department

RJM/cas

TAITO AMERICA CORPORATION

GAMES:

"Space Chaser Upright"
"Lunar Rescue Upright"

SUBJECT:

FALSE CREDITS

SYMPTOM:

Game will add one credit for no apparent reason. The game can then be started without adding a count to the coin meter. Since the meter reading and the cash box total equaled out, the condition could go on unnoticed.

CAUSE:

Transient static of any magnitude causes the condition. However, it may not be evident if you try to simulate it on location. Symptom appears in all types of locations, even areas that don't normally have static problems.

REMEDY:

Obtain two pieces of green 16 ga wire, one 24" long and one 40" long and 3 #6 ring terminals.

1. Remove power from game.
2. Terminate one end of the 24" wire to a ring terminal. Terminate the other end of 24" and one end of 40" wire to a ring terminal. Terminate the remaining end of the 40" wire to a ring terminal.
3. Install the free end of the 24" wire to the monitor chassis frame at any sheet metal screw. Run the other end of the 24" wire down to the logic board chassis and fasten it to one of the screws that mount the chassis to the cabinet side. Run the remaining end of the 40" wire over to the metal "cage" of the switching regulator and attach the ring terminal to any one of the 4 screws that attach the cage to the power supply board.
4. Be sure all other ground wires in the unit are secure.
5. Power up the game and check play of game.

All Space Chaser and Lunar Rescue games with Serial No's. from 78,453 to 101,019 should have this correction performed. If you do not have the required parts, they are available from your Taito distributor free of charge by asking for Taito Part No. 840011 or by calling the Taito toll-free service hot line - 800-323-0666 for same day mailing of this kit free of charge.