CGA/VGA JAMMA

SLASSICAL GAME COLLECTION

I. PCB DIP Switch Settings

D	IP SW3	1	2	3	4
Screen Orientation	Normal	OFF			
Scient Officiation	Flip Screen	ON			
Display Mode	CGA-15.75Khz		OFF		
(CRT)	VGA-31.5Khz		ON		***************************************
High Score Saver	Disabled			OFF	
Ingli ocole bavel	Enabled			ON	

II. System Setup

Keep **TEST SW** or **SERVICE SW** pressed and power on to enter system setup mode or system test mode.

The first page is **Screen Test**. You may tune your screen size at this page or press TEST SW to enter next page.

If high score saver is supported and enabled, the second page is **Clear High Score**. You may clear all saved high scores by pressing both START and S1 buttons. Press TEST SW to enter next page or press SERVICE SW to return last page.

The next page is **System DIPSW Setup**. Use joystick to move cursor or S1 buttons to switch ON/OFF. The system DIPSW is shown below:

System DIPSW Setup for All Amusement PCBs

	DIP SW1	1	2	3	4	5	6	7	8
	1 coin 1 credit	OFF	OFF	OFF	OFF				
<u>,-</u>	1 coin 2 credit	ON	OFF	OFF	OFF				
	1 coin 3 credit	OFF	ON	OFF	OFF				
	1 coin 4 credit	ON	ON	OFF	OFF				
	2 coin 1 credit	OFF	OFF	ON	OFF				
:	2 coin 2 credit	ON	OFF	ON	OFF				
	2 coin 3 credit	OFF	ON	ON	OFF				
Coin 1	2 coin 4 credit	ON	ON	ON	OFF				
Com i	3 coin 1 credit	OFF	OFF	OFF	ON				
	3 coin 2 credit	ON	OFF	OFF	ON				
	3 coin 3 credit	OFF	ON	OFF	ON				
	3 coin 4 credit	ON	ON	OFF	ON				
	4 coin 1 credit	OFF	OFF	ON	ON				
	4 coin 2 credit	ON	OFF	ON	ON				
	4 coin 3 credit	OFF	ON	ON	ON				
	4 coin 4 credit	ON	ON	ON	ON				

	1 coin 1 credit		. (OFF	OFF	OFF	OFF
	1 coin 2 credit			ON	OFF	OFF	OFF
-	1 coin 3 credit		(OFF	ON	OFF	OFF
	1 coin 4 credit			ON	ON	OFF	OFF
	2 coin 1 credit		(OFF	OFF	ON	OFF
	2 coin 2 credit			ON	OFF	ON	OFF
	2 coin 3 credit		(OFF	ON	ON	OFF
Coin 2	2 coin 4 credit			ON	ON	ON	OFF
Coin 2	3 coin 1 credit		(OFF	OFF	OFF	ON
	3 coin 2 credit			ON	OFF	OFF	ON
	3 coin 3 credit	-		OFF	ON	OFF	ON
	3 coin 4 credit			ON	ON	OFF	ON
	4 coin 1 credit			OFF	OFF	ON	ON
	4 coin 2 credit			ON	OFF	ON	ON
	4 coin 3 credit		1	OFF	ON	ON	ON
	4 coin 4 credit			ON	ON	ON	ON

I	DIP SW2	1	2	3	4	5	6	7	8
Demo Music	Yes	OFF							
Demo Music	No	ON							
Game	No		OFF						
Demo Sound	Yes		ON						,
Demo Music	Mode1			OFF					
Mode	Mode2			ON					
E Dl	No				OFF				
Free Play	Yes				ON				
	Upright/1 Joystick					OFF	OFF		
C-1	Cocktail					ON	OFF		
Cabinet	Upright/2 Joysticks					OFF	ON		
	Cocktail					ON	ON		

Each game can be enabled or disabled respectively. Disabled games would not be shown for playing. Press setup to finish this step or press TEST SW to enter followed pages for DIPSW setup of each game or SERVICE SW to return last page.

The last two pages are **Volume Adjust** and **I/O Test**. You may adjust audio volume or diagnose PCB I/O status at these two pages.

For system test mode, only Screen Test and I/O Test pages are included.


III. JAMMA Wire Map

Part Side			Solder Side
GND	1	1	GND
GND	2	2	GND
+5V	3	3	+5V
+5V	4	4	+5V
	5	5	
+12V	6	6	+12V
	7	7	
1P COIN METER	8	8	2P COIN METER
	9	9	
SPEAKER +	10	10	SPEAKER -
	11	11	
VIDEO R	12	12	VIDEO G
VIDEO B	13	13	VIDEO SYNC
GND	14	14	SERVICE
TEST	15	15	
1P-COIN	16	16	2P-COIN
1P-START	17	17	2P-START
1P-UP	18	18	2P-UP
1P-DOWN	19	19	2P-DOWN
1P-LEFT	20	20	2P-LEFT
1P-RIGHT	21	21	2P-RIGHT
1P-S1	22	22	2P-S1
1P-S2	23	23	2P-S2
1P-S3	24	24	2P-S3
	25	25	
	26	26	,
GND	27	27	GND
GND	28	28	GND

PS: The PCB voltage of +5V pin CAN NOT exceed +5.5V.

Game List


Ms Pacman




Galaga




Frogger




Donkey Kong




Donkey Kong Junior




Donkey Kong 3



Galaxian




Dig Dug



Crush Roller




Mr. Do



Space Invaders



Pacman



Galaga3



Gyruss



Tank Battalion




1942




Ladybug




Burger Time




Mappy



Centipede




Millipede




JR Pacman



Pengo



Phoenix




Time Pilot



Super Cobra




Hustler




Space Panic




Super Breakout



New Rally X



Arkanoid



Qix



Juno Frist



Xevious



Mr. Do's Castle



Moon Cresta




Pinball Action



Scramble



Super Pacman



Ms Pacman DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	8
,	5	OFF	OFF						
Life	3	ON	OFF						
Life	2	OFF	ON						
	1	ON	ON						
	None			OFF	OFF				
Extra lifa	20000			ON	OFF				
Extra life	15000			OFF	ON				
	10000			ON	ON				
Difficulty	Easy					OFF			
Difficulty	Hard					ON			
Speed	Normal						OFF		
Speed	Fast						ON		
Ms Pacman	Heart						***************************************	OFF	
Bean	Dot					VA		ON	

Galaga DIPSW Setup

<u>umaga</u>			$\sim \cdot \cdot \cdot$	\sim		~ F	7						
· D)IP	SW1				1	2	3°	4	5	6	7	8
]	Easy		0	FF	OFF						
Difficulty		H	ardest		O	N	OFF						
Difficulty		I	Hard		O	FF	ON						
		M	edium	l	O	N	ON						
Continuous			No					OFF	***************************************				
Shooting			Yes					ON					
		30k	80k			30	30k		OFF	OFF	OFF		
	B 20k 80k 80k		B	30	k 150l	150k	ON	OFF	OFF				
	O	O 30k 120k 120k			30	k 1201	ζ.	OFF	ON	OFF			
Extra Life	N U	20k	60k	60k	Ü	30	k 100l	100k	ON	ON	OFF		
Extra Life	$\ddot{\mathbf{s}}$	20k	60k		2	30	k 150l	C	OFF	OFF	ON		
	1	20k	70k	70k	 ~	30	k 1201	120k	ON	OFF	ON		
		30k	100k	100k	1	30	k 100l	ζ.	OFF	ON	ON		
		(1)	Vone)						ON	ON	ON		
Life		5 (b	onus2	2)								OFF	OFF
		3 (b	onus l)								ON	OFF

4 (bonus1)	 			OFF	ON
2 (bonus1)				ON	ON

D	IP SW2	1	2	3	4	5	6	7	8
Bullet Speed	Normal	OFF							,
	Fast	ON							

Frogger DIPSW Setup

DIP	SW1	1 1	2	3	4	5	6	7	8
	3	OFF	OFF						
Life	7	ON	OFF						
Lile	5.	OFF	ON					,	
	3	ON	ON						

Donkey Kong DIPSW Setup

		1	2	3	4	5	6	7	8
	3	OFF	OFF						
Life	4 5 6 7000 10000 15000	ON	OFF						
Life	5	OFF	ON						
	6	ON	ON						
	7000			OFF	OFF				
Extra Life	10000			ON	OFF				
Extra Life	15000			OFF	ON				
	20000			ON	ON				

Donkey Kong Junior DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	8
	3	OFF	OFF						
Life	4	ON	OFF						
Lile	5	OFF	ON						
	6	ON	ON						
	7000			OFF	OFF				
Extra Life	10000			ON	OFF				
EXIIA LIIE	15000			OFF	ON				
	20000			ON	ON				

Donkey Kong 3 DIPSW Setup

DIP		1	2	3	4	5	6	7	8
	3	OFF	OFF						
Life	4	ON	OFF						
Life	5	OFF	ON						
	6	ON	ON						
	30000			OFF	OFF				
Extra Life	40000			ON	OFF				
EXIIA LIIE	50000			OFF	ON				
	None			ON	ON				

	30000	OFF	OFF		
Additional	40000	ON	OFF		
Bonus	50000	OFF	ON		
	None	ON	ON		
	Easy			OFF	OFF
Difficulty	Medium			ON	OFF
Difficulty	Hard			OFF	ON
	Hardest			ON	ON

Galaxian DIPSW Setup

			. 4						
DIP	DIP SW1		2	3	4	5	6	7	8
	7000	OFF	OFF						
Extra Life	10000	ON	OFF						
Extra Life	12000	OFF	ON		***************************************				
	20000	ON	ON						
Life	2			OFF					
Life	3			ON					

Dig Dug DIPSW Setup

	SW1	1	2	3	4	5	6	7	8
Continue	No	OFF						OFF	
Continue	Yes	ON		·					
	Easy		OFF	OFF				OFF	
Difficulty	Medium		ON	OFF					
Difficulty	Hard		OFF	ON					
	Hardest		ON	ON					
	None				OFF	OFF	OFF		
	20k 70k 70k				ON	OFF	OFF		
	10k 50k 50k				OFF	ON	OFF		
Extra Life	20k 60k				ON	ON	OFF		
LAHA LHC	10k 40k 40k				OFF	OFF	ON		
	10k 40k				ON	OFF	ON		
	20k 60k 60k				OFF	ON	ON		
	10k				ON	ON	ON		
,	· 3							OFF	OFF
Life	5							ON	OFF
Liic	1							OFF	ON
	2							ON	ON

Crush Roller DIPSW Setup

DIP S	DIP SW1		2	3	4	5	6	7	8
	3	OFF	OFF						
Life	4	ON	OFF						
Life	5	OFF	ON						
•	6	ON	ON						
Difficulty	Difficulty Easy			OFF					
Difficulty	Hard			ON				7	

Mr. Do DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	8
	Easy	OFF	OFF						
Diffi aultu	Medium	ON	OFF						
Difficulty	Hard	OFF	ON						
	Hardest	ON	ON						
C-ssial	Easy			OFF					
Special	Hard			ON					
T	Easy				OFF				
Extra	Hard				ON				
	3					OFF	OFF		
T :£-	4					ON	OFF		
Life	5					OFF	ON		
	2					ON	ON		

Space Invaders DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	8
	3	OFF	OFF						
T :C-	4	ON	OFF			,			
Life	5	OFF	ON						
	6	ON	ON						
T T :6-	1500			OFF					
Extra Life	1000			ON					
Mada	Color.				OFF				
Mode	B&W				ON				

Pacman DIPSW Setup

DIP		1	2	3	4	5	6	7	8
	5	OFF	OFF						
r :c-	3	ON	OFF						
Life	2	OFF	ON			ā			
	1	ON	ON						
	None			OFF	OFF				
Extra Life	20000			ON	OFF				
Extra Life	15000			OFF	ON				
	10000			ON	ON				
D:66:16	Easy					OFF			
Difficulty	Hard					ON			1
Clarat Name	Normal						OFF		
Ghost Name	Alternate						ON		
C1	Normal							OFF	
Speed	Fast								

Galaga3 DIPSW Setup

ralagas	عقره	L D V	Y 13	C C C C							
DII	SW1			1	2	3	4	5	6	7	8
	0	(Ea	siest)	OFF	OFF	OFF					
	1			ON	OFF	OFF					
	2			OFF	ON	OFF					
Difficulty	3			ON	ON	OFF					
Difficulty	4			OFF	OFF	ON					
	5			ON	OFF	ON					
	6			OFF	ON	ON					
	7	(Ha	rdest)	ON	ON	ON					
		3					OFF	OFF			
T :C-		2					ON	OFF			
Life		4					OFF	ON			
		5					ON	ON			
	100k	300k	600k						OFF	OFF	OFF
	150k	400k							ON	OFF	OFF
	150k	400k	900k						OFF	ON	OFF
The same Title	100k	300k	300k						ON	ON	OFF
Extra Life	50k	200k	300k						OFF	OFF	ON
	50k	150k	600k						ON	OFF	ON
	50k	150k	300k						OFF	ON	ON
	30k	150k	600k						ON	ON	ON

Gyruss DIPSW Setup

DIPS			1	2	3	4	5	6	7	8
	2	}	OFF	OFF						
· Life	4	ļ	ON	OFF						
Life	5	5	OFF	ON					,	
	3	3	ON	ON						
Extra Life	30k	60k			OFF					
Extra Life	40k	70k			ON					
	1(E	asiest)				OFF	OFF	OFF		
	2					ON	OFF	OFF		
	3					OFF	ON	OFF		
Difficulty	4					ON	ON	OFF		
Difficulty	5(A	verage)				OFF	OFF	ON		
	6					ON	OFF	ON		
	7					OFF	ON	ON		
	8(H	ardest)				ON	ON	ON		

Tank Battalion DIPSW Setup

DIP		1	2	3	4	5	6	7	8
	None	OFF	OFF						
Estas Life	20000	ON	OFF	,					
Extra Life	15000	OFF	ON						
	10000	ON	ON						

Life	2	OFF		
Life	3	ON		

1942 DIPSW Setup

DIP		1	2	3	4	5	6	7	8
	20k 80k	OFF	OFF						
Extra Life	20k 100k	ON	OFF						
Extra Life	30k 80k	OFF	ON						
	30k 100k	ON	ON						
	3			OFF	OFF				
Life	1			ON	OFF				
Life	2			OFF	ON				
	5			ON	ON				
	Normal					OFF	OFF		
Difficulty	Easy					ON	OFF		
Difficulty	Hard					OFF	ON		
	Hardest					ON	ON		

Ladybug DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	8
	Easy	OFF	OFF						
Difficulty	Medium	ON	OFF						
Difficulty	Hard	OFF	ON						
	Hardest	ON	ON					-	
High Score	10 Letters			OFF					
Names	3 Letters			ON		·····			
Life	3				OFF	****			
LITE	5				ON				

Burger Time DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	8
Life	3	OFF							
Life	5	ON							
	10000		OFF	OFF					
Extra Life	15000		ON	OFF					
Extra Life	20000		OFF	ON					
	30000		ON	ON					
Enemies	4				OFF				
Ellelines	6				ON				
End of Lever	No					OFF			
Pepper	Yes					ON			

Mappy DIPSW Setup

DIP S	W1	1	2	3	4	5	6	7	8
	3	OFF	OFF						
Life	*5	ON	OFF						
Life	1	OFF	ON						
	2	ON	ON				***************************************		

	*30k 80k 20k 70k		OFF	OFF	OFF			
	*30k 100k 20k 60k		ON	OFF	OFF			
	*30k 120k 20k 80k		OFF	ÓN	OFF			
	*30k 30k 100k		ON	ON	OFF			
Extra Life	*40k 20k		OFF	OFF	ON			
	*30k 100k 100k 20k 70k 70k		ON	OFF	ON			
	*40k 120k 120k 20k 80k 80k		OFF	ON	ON			
	None		ON	ON	ON			
	A					OFF	OFF	OFF
	В					ON	OFF	OFF
	С					OFF	ON	OFF
Rank	D					ON	ON	OFF
Kank	Е					OFF	OFF	ON
,	F					ON	OFF	ON
	G					OFF	ON	ON
	Н					ON	ON	ON

Centipede DIPSW Setup

DIP		1	2	3	4	5	6	7	8
	English	OFF	OFF						
Languaga	German	ON	OFF						
Language	French	OFF	ON						
	Spanish	ON	ON						
	2 .			OFF	OFF				
Life	3			ON	OFF		٠		
Life	4		,	OFF	ON				
	5			ON	ON				
	10000					OFF	OFF		
Extra Life	12000					ON	OFF		
Extra Life	15000					OFF	ON		
	20000					ON	ON		
D:ff: aultu	Easy							OFF	
Difficulty	Hard							ON	
Move Cood	Normal								OFF
Move Speed	Fast								ON

Millipede DIPSW Setup

DIP		1	2	3	4	5	6	7	8
Millipada Haad	Easy	OFF							
Millipede Head	Hard	ON							
Beetle	Easy		OFF						
Deede	Hard		ON						
	2			OFF	OFF				
r :c-	3			ON	OFF				
Life	4			OFF	ON				
	5			ON	ON				

	12000	OFF	OFF		
Extra Life	15000	ON	OFF		
Extra Life	20000	OFF	ON		
	None	ON	ON		
Cmidon	Easy			OFF	
Spider -	Hard			ON	
Starting Score	No				OFF
Select	Yes				ON

DIP	SW2	1	2	3	4	5	6	7	8
	English	OFF	OFF						
Languaga	German	ON	OFF						
Language	French	OFF	ON						
	Spanish	ON	ON						
	0			OFF	OFF				
Bonus	0 1x			ON	OFF				
Donus	0 1x 2x			OFF	ON				
	0 1x 2x 3x			ON	ON				

JR Pacman DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	8
	1	OFF	OFF						
Life	2	ON	OFF						
Life	3	OFF	ON						
	5	ON	ON						
	10000			OFF	OFF				
Extra Life	15000			ON	OFF				
Extra Life	20000			OFF	ON				
	30000			ON	ON				
Difficulty	Normal					OFF			
Difficulty	Hard					ON			
Speed.	Normal						OFF		
speed.	Fast						ON		

Pengo DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	8
Extra Life	50000	OFF							
Lana Life	30000	ON				•			
	2		OFF	OFF					
Life	3		ON	OFF					
Life	4		OFF	ON					
	5		ON	ON					
	Easy				OFF	OFF			
Difficulty	Medium				ON	OFF			
Difficulty	Hard				OFF	ON			
	Hardest				ON	ON			

Machine Set	Set1			OFF	
Macinile Set	Set2			ON	

Phoenix DIPSW Setup

DIP	SW1		1	2	3	4	5	6	7	8
		3	OFF	OFF						
T :fo		4	ON	OFF						
Life		5	OFF	ON						
		6	ON	ON						
	3K	30K			OFF	OFF				
Extra Life	4K	40K			ON	OFF				
Extra Life	5K	50K			OFF	ON				
	6K	60K			ON	ON				

Time Pilot DIPSW Setup

HIHHE HIH		<u> </u>	V 134	- a an II-	,					
DIP	SW1		1	2	3	4	5	6	7	8
	3	3	OFF	OFF						
Life	4		ON	OFF						
Life	4	5	OFF	ON						
	4.	5	ON	ON						
Extra Life	10k	50k			OFF					
Extra Life	20k	60k			ON					
	1(Eas	iest)				OFF	OFF	OFF		
	2					ON	OFF	OFF		
	3					OFF	ON	OFF		
Difficulty	4					ON	ON	OFF		
Difficulty	5(Ave	erage)				OFF	OFF	ON		
'	6					ON	OFF	ON		
	7					OFF	ON	ON		
	8(Hai	dest)				ON	ON	ON		

Super Cobra DIPSW Setup

/ 			de esta o a caracte						
DIP S	W1	1	2	3	4	5	- 6	7	8
Continue	Yes	OFF							
(Single Game Only)	No	-ON							
Life	4		OFF						
Lite	3		ON						

Hustler DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	8
Life 2	OFF								
Life	1	ON							

Space Panic DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7 -	8
Extra Life	3000	OFF							
Exua Lile	5000	ON							

	I ifa	3	OFF		
-	Liic	4	ON		

Super Breakout DIPSW Setup

	DIP S	SW1		1	2	3	4	5	6	7	8
Mode		Col	or	OFF							
IVIOUC	, [B&	W	ON							
Life		3			OFF						***************************************
Life	ſ	5			ON						******
		Medi	um			OFF	OFF				
Move Sp	book	Slo	w			ON	OFF				
Move Sp	ccu	Fas	st			OFF	ON				
		Very	Fast			ON	ON				
		None						OFF	OFF	OFF	
	200P	200C	200D					ON	OFF	OFF	
	400P	300C	400D					OFF	ON	OFF	
Time *	600P	400C	600D					ON	ON	OFF	
1 ime "	900P	700C	800D					OFF	OFF	ON	
	1200F	900C	1000D				-	ON	OFF	ON	
	1600F	1100C	1200D			4	,	OFF	ON	ON	
	2000F	1400C	1500D					ON	ON	ON	

* Note: P: Progressive C: Cavity D: Double

S1 Button : Select Progressive S2 Button : Select Cavity S3 Button : Select Double

New Rally X DIPSW Setup

DI	P SW1		1	2	3	4	5	6	7	8
	1	None None	OFF	OFF						
Extra Life		20k	ON	OFF						
EXII & EMC		40k	OFF	ON						
	3Cars 20 4Cars	0k/120k 60k	ON	ON						
Life	3				OFF					
Liic	4				ON					

Arkanoid DIPSW Setup

DIP	SW1	1	2	3	4	5	6	7	. 8
Continue	No	OFF							
Continue	Yes	ON							
Difficulty	Easy		OFF						
Difficulty	Hard		ON						
Extra Life	20k 60k 60k			OFF					
Extra Life	20k			ON					
Life	3				OFF				
Life	5				ON				

	Normal	OFF	OFF	
M C1	Slow	ON	OFF	
Move Speed	Fast	OFF	ON	
	Very Fast	ON	ON	

Qix DIPSW Setup

DIP		1	2	3	4	5	6	7	8
	5	OFF	OFF						
Life	. 4	ON	OFF						
Life	3	OFF	ON						
	2	ON	ON						
	60%			OFF	OFF	OFF			·
	65%			ON	OFF	OFF			
	70%			OFF	ON	OFF			
Threshold	75%			ON	ON	OFF			
Thieshold	80%			OFF	OFF	ON			
	85%			ON	OFF	ON			
	90%	<u> </u>		OFF	ON	ON			
	95%			ON	ON	ON			
	60						OFF	OFF	OFF
	55		·				ON	OFF	OFF
	50						OFF	ON	OFF
TT:	45						ON	.ON	OFF
Time	40						OFF	OFF	ON
	35						ON	OFF	ON
	30						OFF	ON	ON
	25						ON	ON	ON

Juno First DIPSW Setup

	SW1	T 1	2	3	4	5	6	7	8
	3	OFF	OFF						
Life	4	ON	OFF						
Life	5	OFF	ON						· .
	3	ON	ON						
	1(Easiest)		-	OFF	OFF	OFF			
	2			ON	OFF	OFF			
	3			OFF	ON	OFF			
Difficulty	4			ON	ON	OFF			
Difficulty	5			OFF	OFF	ON			
	6			ON	OFF	ON			
	7			OFF	ON	ON			
	8(Hardest)			ON	ON	ON			

Xevious DIPSW Setup

Annual Control of the	IP SW1	T 1	2	3	4	5	6	7	8
٠.	3	OFF	OFF						
Life	1	ON	OFF						
	2	OFF	ON					***************************************	
	5	ON	ON			-			
Flags Award	Yes			OFF					
Bonus Life	No			ON					
	Normal				OFF	OFF			
Difficulty	Easy				ON	OFF			
Difficulty	Hard				OFF	ON			
	Hardest				ON	ON			
	20k60k60k / 20k70k70k						OFF	OFF	OFF
	10k40k40k / 10k50k50k						ON	OFF	OFF
	10k50k50k / 20k50k50k						OFF	ON	OFF
Extra Life	20k50k50k / 20k60k60k						ON	ON	OFF
Datitu Dire	20k70k70k / 20k80k80k						OFF	OFF	ON
	20k80k80k/30k100k100k						ON	OFF	ON
	20k 60k/20k 80k						OFF	ON	ON
	None	·					ON	ON	ON
DIP SW2		1	2	3	4	5	6	7	8
Set 1		OFF	OFF						
Machine Set	Set 2	ON	OFF						
Machine 36	Set 3	OFF	ON						
	Super Xevious	ON	ON						

Mr. Do's Castle DIPSW Setup

DIP SW	1	1	2	3	4	5	6	7	8
	Easy	OFF	OFF						
Difficulty	Medium	ON	OFF						
Difficulty	Hard	OFF	ON						
	Hardest	ON	ON						
Machine Set	Set 1			OFF					
Macinic Set	Set 2			ON					
Advance Level On	Off				OFF				
Getting Diamond	On				ON				
Extra Life	Easy					OFF			
Extra Life	Hard					ON			
	3						OFF	OFF	
Life	4						ON	OFF	
	5						OFF	ON	
	2						ON	ON	

Moon Cresta DIPSW Setup

DIP SW1		1	2	3	4	5	6	7	8
Extra Life	30000	OFF							
	50000	ON							
Machine Set	Set 1		OFF						
	Set 2		ON						

Pinball Action DIPSW Setup

DIP SW1		1	2	3	4	5	6	7	8
•	Mode 1	OFF	OFF						
* Control	Mode 2	ON	OFF						
* Control	Mode 3	OFF	ON						
	Mode 4	ON	ON						
	3					OFF	OFF		
т :£-	4					ON	OFF		
Life	5					OFF	ON		
	2					ON	ON		

Control	Left Paddle	Right Paddle	Shoot	Shake
Mode 1	LEFT	RIGHT	S1	S2
Mode 2	S1	. S2	UP/DOWN	LEFT/RIGHT
Mode 3	LEFT	RIGHT	UP	S1
Mode 4	LEFT	RIGHT	UP	DOWN


	DIP SV	V2		1	2	3	4	5	6	7	8
	70k	200k		OFF	OFF	OFF					
Extra Life	70k	200k	1000k	ON	OFF	OFF					
	100k			OFF	ON	OFF					
	100k	300k		ON	ON	OFF					
Extra Life	100k	300k	1000k	OFF	OFF	ON					
	200k			ON	OFF	ON					
	200k	1000k		OFF	ON	ON					
		None		ON	ON	ON					
Extra		Easy					OFF				
Exua	Hard					ON					
		Easy						OFF	OFF		
Difficulty		Medium						ON	OFF		
(Flippers)		Hard						OFF	ON		
		Hardes	t .					ON	ON		
		Easy								OFF	OFF
Difficulty (Outlans)]	Mediur	n							ON	OFF
		Hard								OFF	ON
		Hardes	t							ON	ON

Scramble DIPSW Setup

DIP SW1		T 1	2	3	4	5	6	7	8
	3	OFF	OFF						
Life	4	ON	OFF						***
Life	5	OFF	ON						
	2	ON	ON						
Machine Set	Set 1			OFF					
	Set 2			ON					

Super Pacman DIPSW Setup

Super	Pacman DI	PSY	W S	etu	P				
	DIP SW1	1	2	3	4	5	6	7	8
	0 (Normal)	OFF	OFF	OFF	OFF				
	1 (Easiest)	ON	OFF	OFF	OFF				
,	2	OFF	ON	OFF	OFF				
	3	ON	ON	OFF	OFF				
	4	OFF	OFF	ON	OFF				
	5	ON	OFF	ON	OFF				
	6 (Medium)	OFF	ON	ON	OFF				
Difficulty	7	ON	ON	ON	OFF				***************************************
Difficulty	8	OFF	OFF	OFF	ON				
	9	ON	OFF	OFF	ON				
	A	OFF	ON	OFF	ON				
	B (Hardest)	ON	ON	OFF	ON				
	C (Easy Auto)	OFF	OFF	ON	ON				•
	D (Auto)	ON	OFF	ON	ON				
	E (Auto)	OFF	ON	ON	ON				
	F (Hard Auto)	ON	ON	ON	ON				
	*30k 100k 30k 100k					OFF	OFF	OFF	
	*30k 120k					ONI	OBB	OEE	
	30k 80k					ON	OFF	OFF	
	*40k 120k 30k 120k					OFF	ON	OFF	
	*30k 100k 100k					ON	ON	OFF	
Extra Life	30k 80k 80k *40k 120k 120k								
	30k 100k 100k					OFF	OFF	ON	
	*30k 30k 120k 120k					ON	OFF	ON	
	*40k					OFF	ON	ON	
	30k								
	None					ON	ON	ON	
Machine	Set 1								OFF
Set	Set 2								ON
DIP SW2		1	2	3	4	5	6	7	.8
	3	OFF	OFF						
Life	1	ON	OFF						
	2	OFF	ON						
	*5	ON	ON						



Game Never Over