

## BILL OF MATERIALS 548 AMPLIFIER

ITEM	PART NO.	VALUE	REMARKS +	ITEM	PART NO.	VALUE	REMARKS
R-1	72246-32	180K	1/2 W. 10%	C-15	76403-341	.0018 MFD	DISC
R-2	72210-32	5.6K	1/2 W. 10%	C-16	76203-17S	.22 MFD	75V.
R-3	72240-32	100K	1/2 W. 10%	C-16 OPT	76333-321	.22 MFD	100V.
R-4	72246-32	180K	1/2 W. 10%	C-17	76501-6	100 MFD	25V.
R-5	72192-32	1K	1/2 W. 10%	C-17 OPT	74432-136	100 MFD	25V.
R-6	72226-31	27K	1/2 W. 5%	C-18	76264	500 MFD	15V.
R-7	72264-32	1 MEG.	1/2 W. 10%	C-19	76691-134	350 MFD	15V.
R-8	72232-32	47K	1/2 W. 10%	C-20	76263	1200 MFD	35V.
R-9	72211-31	6.2K	1/2 W. 5%	C-20 OPT	76622	1200 MFD	35V.
R-10	72232-32	47K	1/2 W. 10%	C-21	76207-27S	.33 MFD	75V.
R-11	72189-31	750 OHM	1/2 W. 5%	C-22			
R-12	72201-31	2.4K	1/2 W. 5%	C-23	76620	3000 MFD	50V.
R-13	72205-31	3.6K	1/2 W. 5%	C-24	76621	2000 MFD	50V. J-1/8 Cans
R-14	72224-32	22K	1/2 W. 10%	C-25	74321-14	.1 MFD	400V.
R-15	72212-32	6.8K	1/2 W. 10%	C-25 OPT	71541-14	.1 MFD	400V.
R-16	72232-32	47K	1/2 W. 10%	C-26	74567-27	.033 MFD	1000V.
R-17	72232-32	47K	1/2 W. 10%	C-27	74581-22	47 MFD	200V.
R-18	72207-31	4.3K	1/2 W. 5%	S-1	125709		D.F.D.T. MONO-STEREO
R-19	72204-32	3.3K	1/2 W. 10%	S-2	125708		D.F.T.T. TREBLE
R-20	72150-32	18 OHM	1/2 W. 10%	S-3	125708		D.F.T.T. BASS
R-21	72184-32	470 OHM	1/2 W. 10%	S-4	121301		D.P.S.T. POWER
R-22	72246-32	180K	1/2 W. 10%	S-5	68770		S.P.D.T. CANCEL
R-23	72226-32	27K	1/2 W. 10%	T-1	131303		LOW POWER
R-24	72192-32	1K	1/2 W. 10%	T-2	126502		DRIVER
R-25	125710	100K	BALANCE	T-3	131304		AUDIO OUTPUT
R-26	72194-32	1.2K	1/2 W. 10%	F-1	71590-48		15 AMP.
R-27	125700	100K	CONTROL	F-2	71590-33		8 AMP.
R-28	72226-32	27K	1/2 W. 10%	F-3	71590-33		8 AMP.
R-29	72204-32	3.3K	1/2 W. 10%	F-4	71590-22		3 AMP.
R-30	72228-32	33K	1/2 W. 10%	F-5	71590-33		8 AMP.
R-31	74903-3	120 OHM	10 W. 5%	SR-1	71588-21		SILICON 3A
R-32	74482-32	1.8 OHM	2 W. 10%	SR-2	71588-21		SILICON 3A
R-33	74826-2	390 OHM	5 W. 10%	SR-3	71588-21		SILICON 3A
R-34	74826-2	390 OHM	5 W. 10%	SR-4	71588-21		SILICON 3A
R-35	72144-32	10 OHM	1/2 W. 10%	VR-1	125711		DUAL SELENIUM-YELLOW
R-36	74818-2	50 OHM	5 W. 10%	VR-2	125712		DUAL SELENIUM-RED
R-37	74899-2	45 OHM	10 W. 10%	RY-5	129547		RELAY D.F.D.T.
R-38	72288-33	10 OHM	1 W. 30%	BR	125989		BULB-BARRETTER
R-39	72190-32	820 OHM	1/2 W. 10%	Q-1, 2	130537-5		GREEN DOT
C-1	76504-2	175 MFD	6V.	Q-3, 4	130537-4		YELLOW DOT
C-1 OPT	74434-132	175 MFD	6V.	Q-5	131262		P-N-P SILICON
C-2	76115-11	.068 MFD	100V.	Q-6, 7	130537-2		RED DOT
C-2 OPT	76327-311	.068 MFD	100V.	Q-6, 7 OPT	130537-3		ORANGE DOT
C-2 OPT	76191-11S	.068 MFD	100V.	Q-6, 7 OPT	130537-4		YELLOW DOT
C-3	76481-6	2 MFD	25V.	C-8, 9	131261		MEDIUM-POWER P-N-P
C-4	76167-11	.0068 MFD	100V.	CLIP	131263		FOR Q-8 AND Q-9
C-5	76333-321	.22 MFD	100V.	Q-10, 11			
C-5 OPT	76203-17S	.22 MFD	75V.	Q-12, 13	125703-2		RED DOT P.A. TRANSISTOR
C-6	76501-2	100 MFD	6V.	Q-10-11	125703-3		ORANGE DOT
C-6 OPT	74432-132	100 MFD	6V.	12-13	125703-4		YELLOW DOT
C-7	76398-141	.0027 MFD	DISC	OPT.	125703-5		GREEN DOT
C-8	76195-11S	.1 MFD	100V.		125703-6		BLUE DOT
C-8 OPT	76305-11	.1 MFD	100V.				
C-9 OPT	76329-311	.1 MFD	100V.				
C-9	76398-141	.0027 MFD	DISC				
C-10	76115-11	.068 MFD	100V.				
C-10 OPT	76327-311	.068 MFD	100V.				
C-10 OPT	76191-11S	.068 MFD	100V.				
C-11	76383-341	.01 MFD	DISC				
C-12	76385-341	.0082 MFD	DISC				
C-13	76199-17S	.15 MFD	75V.				
C-13 OPT	76331-321	.15 MFD	100V.				
C-14	76167-11	.0068 MFD	100V.				