

SECTION G

BILL OF MATERIALS 550 AMPLIFIER

ITEM NO.	PART NO.	VALUE	REMARKS ±	ITEM NO.	PART NO.	VALUE	REMARKS
R1	72246-32	180K	1/2 W. 10%	C16	76203-17S	.22 MFD	75V
R2	72210-32	5.6K	1/2 W. 10%	C16 OPT	76333-321	.22 MFD	100V
R3	72240-32	100K	1/2 W. 10%	C17	76686-135	100 MFD	25V
R4	72246-32	180K	1/2 W. 10%	C17 OPT	74432-136	100 MFD	25V
R5	72192-32	1K	1/2 W. 10%	C18	76811	500 MFD	25V
R6	72237-31	75K	1/2 W. 5%	C19	76806	150 MFD	35V
R7	72262-31	820K	1/2 W. 5%	C20	76165-11	.0056 MFD	100V
R8	72232-32	47K	1/2 W. 10%	C21	76207-27S	.33 MFD	75V
R9	72211-31	6.2K	1/2 W. 5%	C22	74581-22	.47 MFD	200V
R10	72237-31	75K	1/2 W. 5%	C23	76620	3000 MFD	55V
R11	72189-31	750 OHM	1/2 W. 5%	C24	76621	2000 MFD	50V
R12	72199-31	2K	1/2 W. 5%	C25	76912	3000 MFD	55V
R13	72205-31	3.6K	1/2 W. 5%	C26	76319-311	.015 MFD	100V
R14	72227-31	30K	1/2 W. 5%	C26 OPT	76175-11S	.015 MFD	100V
R15	72220-32	15K	1/2 W. 10%	S1	125709	D.P.D.T.	
R17	72235-31	62K	1/2 W. 5%	S2	125708	D.P.T.T.	
R18	72207-31	4.3K	1/2 W. 5%	S3	125708	D.P.T.T.	
R19	72212-32	6.8K	1/2 W. 10%	S4	121301	D.P.S.T.	
R20	72150-32	18 OHM	1/2 W. 10%	S5	68770	S.P.D.T.	
R21	72184-32	470 OHM	1/2 W. 10%	T1	134316	LOW-VOLTAGE	
R22	72246-32	180K	1/2 W. 10%	T2	134305	DRIVER	
R23	72226-32	27K	1/2 W. 10%	T3	134431	AUDIO	
R24	72192-32	1K	1/2 W. 10%	F1	71590-48	15 AMP	
R25	125710	100K	BALANCE	F2	71590-22	3 AMP	
R26	72194-32	1.2K	1/2 W. 10%	F3	71591-23	3 AMP	SLO BLO
R27	125700	100K	CONTROL	F4	71591-23	3 AMP	SLO BLO
R28	72226-32	27K	1/2 W. 10%	F5	71591-23	3 AMP	SLO BLO
R29	74815-2	8 OHM	5 W. 10%	F6	71591-23	3 AMP	SLO BLO
R30	74844-2	.5 OHM	5 W. 10%	F7	71590-33	8 AMP	
R31	74903-3	120 OHM	10 W. 5%	VR-1	133932	DUAL SELENIUM - YELLOW	
R32	74486-32	2.7 OHM	2 W. 10%	VR-2	133907	DUAL SELENIUM - RED	
R33	74546-32	820 OHM	2 W. 10%	SR1	71588-21	SILICON 3A	
R34	74826-2	390 OHM	5 W. 10%	SR2	71588-22		
R35	72144-32	10 OHM	1/2 W. 10%	SR3	OPT.		
R36	72254-32	390K	1/2 W. 10%	SR4			
C1	76689-132	175 MFD	6V	SR5			
C1 OPT	74434-132	175 MFD	6V	SR6			
C2	76115-11	.068 MFD	100V	Q1 & Q2	130537-5	GREEN DOT	
C2 OPT	76191-11S	.068 MFD	100V	Q3 & Q4	130537-4	YELLOW DOT	
C2 OPT	76327-311	.068 MFD	100V	Q5	131262	P-N-P SILICON	
C3	76481-6	2 MFD	25V	Q6 & Q7	130537-5	N-P-N SILICON GREEN DO	
C4	76163-11S	.0047 MFD	100V	Q8 & Q9	131777	DRIVER	
C5	76185-11S	.039 MFD	100V	Q10 & Q11	125703	RED, ORN., YEL., GRN.,	
C5 OPT	76324-311	.039 MFD	100V	Q12 & Q13			OR BLUE
C6	76686-132	100 MFD	6V	J-1		112730	WIRE - FORMED
C6 OPT	74432-132	100 MFD	6V				
C7	76387-141	.0068 MFD	DISC				
C8	76115-11	.068 MFD	100V				
C8 OPT	76327-311	.068 MFD	100V				
C8 OPT	76191-11S	.068 MFD	100V				
C9	76398-141	.0027 MFD	DISC				
C10	76115-11	.068 MFD	100V				
C10 OPT	76327-311	.068 MFD	100V				
C10 OPT	76191-11S	.068 MFD	100V				
C11 & C12	76401-341	.0022 MFD	DISC				
C13	76191-11S	.068 MFD	100V				
C13 OPT	76327-311	.068 MFD	100V				
C13 OPT	76115-11	.068 MFD	100V				
C14	76171-11S	.01 MFD	100V				
C15	76419-341	.00047 MFD	DISC				